

# Contractor Series

the choice for value and reliability

chain drive  
**1/2 HP**  
garage door opener

## 3255

**rugged...reliable...  
chain drive**

A durable 1/2 HP motor combined with industrial-strength chain drive provides steady performance.


**now with ERT™  
technology**

Provides superior protection from outside radio signal interference, now operating at 315MHz.



**multi-function  
control panel**

Controls your garage door and turns opener lights on/off from inside garage. Locks out all outside radio signals while you're away. Includes an adjustable light timer and an illuminated oversized push button for convenience.



**Security+®  
remote control**

With rolling code technology, you are assured of a new code with every use. Every time you push the button, the code automatically rolls over to any one of more than 100-billion new codes, never to be repeated.

CHAMBERLAIN®

# LiftMaster®

PROFESSIONAL

## features that make a difference

### brighter light...better control

100 watts of light. Adjustable 1/2 to 4 1/2 minute light delay. Plus, hinged lens allows easier bulb replacement.



### exclusive! The Smart Garage Door Opener\*

Lets you electronically program security codes from the multi-function control panel or the powerhead.

### Quick-Connect™ terminals

Push-in wiring for quicker installation.



The in-vehicle universal remote control. See your automobile dealer for availability.

## all the safety you need



### The Protector System\*

Projects an invisible light beam across garage door opening. If anything interrupts the beam while the door is closing, door automatically reverses before making contact. If beam is obstructed, door will not close.

### equipped with PosiLock®

Once your garage door is down, it's securely locked with PosiLock®, a patented Chamberlain® feature. An intruder cannot gain access.



### manual release handle

In a power failure, this feature releases the door for manual operation.

**4-YEAR MOTOR WARRANTY**

#### MOTOR

Horsepower: 1/2  
RPM: 1,825  
Thermal Protection: Automatic  
Lubrication: Permanent

#### DRIVE MECHANISM

Drive Means: Full Chain  
Reduction Means: Gear 16:1  
Door Linkage: Adjustable Door Arm

#### LOGIC TYPE

Solid-State Microcontroller  
with Built-in Surge Suppressor

#### DIMENSIONS

Installed Length: 124"  
Maximum Door Opening: 7' 6"  
Travel Rate: Approximately 7"/Second  
Headroom Clearance Required: 2"  
\*Up to 10' with optional 6', 8' or 10' rails.

#### SHIPPING WEIGHT

Head: 29 lbs.  
Rail: Full Chain—17 lbs.

#### ADJUSTMENTS

Force: Independent External  
Up and Down  
Limit: External

#### ELECTRICAL

Voltage: 120V AC, 60Hz  
Wattage: 540  
Current Rating: 4.5  
UL Listings: Yes  
Length of Line Cord: 4' (3-prong)

#### SECURITY+® RADIO CONTROLS

Coding System: Smart Receiver  
Code Button and Indicator Light  
Operating Range: 150' (approximately)  
Operating Temperature: -40°F to 150°F  
Battery (remote control): 3-volt  
Frequency: 315MHz  
371LM Standard Remote with Security+® Anti-Burglary Coding

#### LIGHTING SYSTEM

Number of Bulbs: 1  
Maximum Wattage: 100  
Length of Light Delay: 4 1/2 Minutes  
Type of Light Delay: Solid-State

#### CONVENIENCE/SAFETY

The Protector System®  
Emergency/Quick Release  
Automatic Trolley Reconnect  
Ventilation/Pet Opening  
Down Safety Reverse  
Up Safety Stop  
Door Open/Beam Broken/Lights On PosiLock®

#### MATERIALS

Chassis: Steel  
Rail: Solid-Steel T  
Trolley: Steel

#### CARTONS

Number of Cartons: 2  
Carton 1 Dimensions: 20" x 12" x 10"  
Carton 1 Contents:  
Multi-Function Control Panel,  
371LM Remote, Garage Door  
Opener Head,  
The Protector System®  
Carton 2 Dimensions: 10' 4" x 5" x 5"  
Carton 2 Contents: Assembled  
Solid-Steel T-Rail

**\*WARNING:** Garage doors and openers can be dangerous if not properly installed, tested and operated. Children should be supervised by an adult whenever in or around the garage area.

#### 4-Year Motor Warranty

One year on all other parts. LiftMaster® garage door openers meet all current state and federal regulations and UL safety regulations as of date of manufacture.

## enhance your lifestyle with optional accessories

### know for sure the door is closed

Lets you know whether the garage door is open or closed from any room in the house. A flashing red light shows the door is open; a glowing green light indicates the door is closed.

### garage door monitor



### enter without a key

Open your garage door without using a remote control and set a temporary entry code for friends and service people.

### wireless keyless entry with Security+®



### walk into a bright garage

It sees you coming! Turns garage door opener lights on automatically when you enter the garage.

### premium motion-detecting control panel



### one control for 2 or 3 garage doors

Open and close up to 3 garage doors, turn opener lights on/off from inside the garage and lock out all remote control radio signals while you're away.

### 2 & 3-door multi-function control panels



### light your home with your remote


Turn on lights or appliances in your home with your garage door opener remote control from inside your car.

### remote light control



CHAMBERLAIN®  
**LiftMaster**  
PROFESSIONAL  
World's #1 Installed Garage Door Opener

THE CHAMBERLAIN GROUP, INC.  
845 Larch Avenue • Elmhurst, IL 60126  
www.liftmaster.com



I.C./F.C.C.  
Certified

©2005 LM 3255 04/05  
The Chamberlain Group, Inc.  
Printed in U.S.A.

LMCA3255